CCGX: Updating firmware

1. Using the right procedure

Depending on the installed firmware version, the update procedure differs.

Running firmware version v1.74 or earlier? An upgrade is needed. Follow the upgrade procedure to v2.00.

Already on firmware version 2.00 or later, continue reading on this page.

2. Update procedure when v2.00 is already installed


There are two ways to update the firmware of a CCGX:

- 1. Update it via the internet, either manually or let it check for new updates every day
- 2. Update it from an microSD-card or USB-stick

2.1 Direct download from the internet

To update from the internet, navigate to: **Settings→ Firmware→Online updates.**

<	Firmware	08:57
Firmware version		v2.00
Build date/time		201612301035
Online updates		>
Offline updates		>
Stored backup firmwar	e	>
<u>الا</u> Pages		⊒ Menu



2.2 microSD-card or USB-stick

Updating with a microSD-card or USB-stick is called 'Offline updating'. Use it when updating a device that is not connected to the internet.

Step 1. Download


Get the latest swu file: https://updates.victronenergy.com/feeds/venus/release/images/ccgx/venus-swu-ccgx.swu

Step 2. Install on an sdcard or usb stick

Store the file in the root folder of a USB stick or microSD card.

Step 3. Insert the device into the CCGX

Note that you will see a warning "Not using media for storing logs". That warning can safely be ignored.



Step 4. Initiate the update

- Navigate to Settings → Firmware → Offline updates.
- Press Check for updates
- If the firmware in the microSD card or USB stick is newer than the running one "Update available" item will appear, press it to start the update process.

〈 Offline updates		09:14
Check for updates on SD/USB		Press to check
Update available	Press to	update to v2.01
Update build date/time		201701131248
<u>ااا</u> Pages		⊒ Menu

DISQUS Comments

View the discussion thread.

From: https://www.victronenergy.com/live/ - **Victron Energy**

Permanent link: https://www.victronenergy.com/live/ccgx:firmware_updating



Last update: 2017-01-18 22:45